

Omni DTF Mini Daily Maintenance Log



Serial Number: _____

Week of : _____

Task	Mon	Tue	Wed	Thu	Fri	Sat	Sun
Omni DTF Mini Daily Startup							
Confirm appropriate level of ink in bottles							
Manually stir white ink at bottom of bottle							
Run the <i>Omni DTF Mini UI</i> program							
Turn on the Omni DTF Mini printer							
Turn on circulation for 5 minutes, then turn off							
Open ink clips then run two printhead cleanings							
Print and evaluate a Nozzle Check test							
<i>If any nozzle check pattern is less than 90% complete, run another printhead cleaning</i>							
<i>If extra printhead cleaning was needed, print another nozzle check and repeat as needed</i>							
Confirm sufficient DTF Powder on film							
Turn on the Dust-Curing Machine (oven)							
Operator Initials:							
Omni DTF Mini Daily Shutdown							
Turn off the Dust-Curing Machine (oven)							
Run a head cleaning							
Empty the waste ink bottle							
Reposition and clamp the 8 ink clips							
Clean the wiper blade & capping station seals							
Flush the capping stations with Super Cleaner							
Fill the capping stations with Super Cleaner							
Clean the printhead mounting plate & undercarriage							
Use the printer's <i>Enter</i> button to Wet Cap							
Turn off the printer							
Wipe down outer equipment surfaces							
Operator Initials:							

Please write the date maintenance was completed. If no maintenance was performed, leave the space blank.

Omni DTF Mini Periodic Maintenance Log

Serial number: _____

Year: _____

Task	Frequency (months)	January	February	March	April	May	June	July	August	September	October	November	December
Clean & lube the carriage rail	Bi-weekly												
Clean the encoder strip	Bi-weekly												
Align the printheads	As needed												
Clean the oven's heat lamps	As needed												
Replace ink tubes	As needed												
Replace absorbing pad	3												
Replace air purifier filter	3												
Replace dampers	6												
Replace wiper blade	6												
Replace capping stations	6												
Replace white ink filter	6												
Replace printheads	12												
Replace circulation pump	18												
Replace encoder strip	12												
Replace oven heating lamps	12												
Replace ink line clip	12												
Replace ink bottles	12-18												
Replace waste pump	18												
Replace manifold	24												

Please write the date maintenance was completed. If no maintenance was performed, leave the space blank.

Note: The above frequencies are suggestions only. Actual maintenance requirements may vary based on usage of your machine. For assistance on determining an appropriate schedule, please contact Tech Support.